

Gasoline Generator
1.2KW

RH-4703

- 98cc, 4-stroke high power 1.2kw engine with outstanding performance
- Large 5 Liter full iron fuel tank provides up to 9 hours of run time
- Includes a selection of outlets for maximum compatibility in your applications including: 220V AC outlets and one (12V) DC outlet
- Includes a voltmeter for measuring output voltage
- Special compact design for ease of use and reliable portability
- Covered, AC protector outlets for added protection
- Minimum sound and vibration in indoor usage
- 100% copper-wound generator head allows continuous operation without overheating
- Low oil alerting system for more protection of motor and longer lifetime
- Ideal for workshops and light-duty industrial usage



Engine	Model	RH-4703
	Model	LB156F
	Type	4stroke Air Cooled Engine
	Displacement	98cc
	Rated Power	3HP
	Ignition System	TCI
	Start	Manual
	Fuel Tank Capacity	5L
	Continuous Working	9h
	Fuel Type	Unleaded Petrol
Generator	Type	Single Phase
	Rated Voltage	220V
	Frequency	50HZ
	Winding Material	Copper
	Rated Amperage	3.9-4.3A
	Rated Power	900-1000W
	Max Power	1200W
	DC Output	12V

Weight	23Kg
Supplied in	Ronix Brown Box
Include	Plug, DC Wire, Spark Plug Wrench, Rubber Feet+nut