

**Portable Gasoline Generator**  
**2800W**

**RH-4728**

- 212cc, 4-Stroke high power 2.8kw engine with outstanding performance
- Large 15 Liter full steel fuel tank provides up to 12 hours of run time at 50% load and 8 hours at full load
- Includes a selection of outlets for maximum compatibility in your applications including: Two 220V AC outlets and one (12V, 6A) DC outlet
- Includes a voltmeter for measuring output voltage
- Special compact design with heavy-duty, never flat wheels for ease of use and reliable portability
- Covered, circuit breaker outlets for added protection
- Minimum sound and vibration in indoor usage
- 100% copper-wound generator head allows continuous operation without overheating
- Low oil alerting system for more protection of motor and longer lifetime



Model	RH-4728
Power	2800W
Voltage	220V
DC Output	12V-6A
Fuel Capacity	15 Litre
Cylinder Capacity	212cc
Noise	68DB@7M>
Full Load Continuous Working	8 Hours
1/2 Load Continuous Working	12 Hours
Weight	39Kg
Supplied in	Ronix Color Box
Includes	DC Wire, Spark Plug Wrench, Funnel