

**Gasoline Generator**  
**3500W**

**RH-4780**

- 212cc, 4-Stroke 4300w engine with considerable performance
- 15 Liter full steel fuel tank provides up to 8.6 hours of run time
- Special compact design for ease of use and better portability
- Circuit breaker outlets for added protection
- Minimum sound and vibration in indoor usage
- 100% copper-wound generator head allows continuous operation without overheating
- Includes one (12V) DC outlets
- Ideal for workshops and light-duty industrial usage



Model	RH-4780		
Generator	Type	Gasoline Generator	
	AC Voltage	220V	
	Rated Amperage	13A	
	Frequency	50Hz	
	Max. Output	3.5KW	
	Rated Output	3.3KW	
	Power Factor	1	
	DC Output	DC12V,8.3A	
	Engine	Model	FC170F-1
		Type	Single Cylinder, 4-Stroke, Forced Air Cooled
Bore×Stroke		70mm×55mm	
Displacement		212cc	
Max. Output		4.3KW /3600RPM	
Fuel		Gasoline	
Fuel tank Capacity		15 Lit	
Rated Continuous Operation		8.6hr	
Lubricating Oil		SAE 10W-30	
Lubricating Oil Capacity		0.6 Liter	
Starting System		Recoil	
Ignition System	T.C.I		
Spark Plug: Type	F7TC/F7RTC		



Engine	Maximum Fuel Consumption Rate	1.74Lit/hr
Dimension	Net Dimension LxWxH	590x430x465mm
	Overall Dimension LxWxH	645x490x530mm
	Net Weight	43.5Kg
	Gross Weight	45.5Kg
Supplied in	Carton	
Include	2 Plug, 1 Spark Plug Sleeve,1 Rod, one 12V DC Output Clip	