

Gasoline Inverter Generator
1200W

RH-4791

- 60cc, 4-stroke high power 1.2kw engine with outstanding performance
- Decreasing weight more than 20% compared with normal gasoline generator for better portability and less occupation
- Produces Output Pure Sine Wave AC and stable voltage to prevent from damaging to sensitive electronics equipment such as cell phone, laptop, and TV etc
- Super quiet as low as 58 dBA
- Equipped with 220V AC outlet and 12V DC outlet
- Economy Mode Switch Reduces wear and fuel consumption by adjusting RPM based on generator load
- The control unit instantly senses overload or short circuit and immediately shuts off engine to protect the generator and the load
- Low Oil Alert Helps to prevent engine damage
- Ideal for electronics equipment, RV, camping and home applications, small power tools



Model	RH-4791	
Generator	Type	Inverter Generator
	AC Voltage	220V-50Hz
	Max. Output	1.2KW
	Rated Output	1.0KW
	Power Factor	1
	DC Output	DC12V 4A
	Engine	Model
Type		Air-cooled, 4 cycle OHV, Gasoline Engine
BorexStroke mmxmm		44x39.5
Displacement		60cc
Max. Output		1.3KW / 5500rpm
Fuel		Regular Automobile Gasoline
Fuel tank Capacity		3.0liters

Engine	Rated Continuous Operation	4.4hr
	Lubricating oil	SAE 10W30
	Lubricating oil Capacity	0.27liter
	Starting System	Recoil Starter
	Ignition system	C.D.I.
	Spark Plug: Type	A5RTC (TORCH)
Dimension	Net dimension LxWxH	448x236x392
	Overall dimension LxWxH	480x255x425
	Net Weight	12Kg
	Gross Weight	15Kg
Supplied in	Ronix Brown Box	
Include	DC wire, Screwdriver, Spark plug wrench	