

**Gasoline Inverter Generator**  
**2000W**

**RH-4792**

- 99cc, 4-stroke high power 2kw engine with outstanding performance
- Decreasing weight more than 20% compared with normal gasoline generator for better portability and less occupation
- Produces Output Pure Sine Wave AC and stable voltage to prevent from damaging to sensitive electronics equipment such as cell phone, laptop, and TV etc
- Super quiet as low as 60 DBA
- Equiped with two 220V AC outlet and one 12V DC outlet
- Economy Mode Switch Reduces wear and fuel consumption by adjusting RPM based on generator load
- The control unit instantly senses overload or short circuit and immediately shuts of engine to protect the generator and the load
- Low Oil Alert Helps to prevent engine damage
- Ideal for electronics equipment, RV, camping and home applications, small power tools



Model	RH-4792	
Generator	Type	Inverter Generator
	AC Voltage	220V-50Hz
	Max. Output	2.0KW
	Rated Output	1.7KW
	Power Factor	1
	DC Output	DC12V 5A
Engine	Model	XY152F-4 / SY152F-4
	Type	Air-cooled, 4 cycle, OHV, Gasoline Engine
	BorexStroke mm×mm	52.4×46
	Displacement	99cc
	Max. Output	2.1KW / 4500rpm
	Fuel	Regular Automobile Gasoline
	Fuel tank Capacity	4.1liters

Engine	Rated Continuous Operation	3.8hr
	Lubricating oil	SAE 10W30
	Lubricating oil Capacity	0.52liter
	Starting System	Recoil Starter
	Ignition system	C.D.I.
	Spark Plug: Type	A5RTC (TORCH)
Dimension	Net dimension LxWxH	525x282x457
	Overall dimension LxWxH	555x315x490
	Net Weight	18.5Kg
	Gross Weight	21.0Kg
Supplied in	Ronix Brown Box	
Include	DC wire, Screwdriver, Spark plug wrench	