

Gasoline Generator

• 223 cc, 4 - Stroke 4900w engine with considerable performance

- 15 Liter full steel fuel tank provides up to 8.6 hours of run time
- Special compact designfor ease of use and better portability
- Circuit breaker outlets for added protection
- Minimum sound and vibration in indoor usage
- 100% copper-wound generator head allows continuous operation without overheating
- Includes one (12V) DC outlets
- Ideal for workshops and light-duty industrial usage

Model	RH-4781	
Generator	Туре	Gasoline Generator
	AC Voltage	220V
	Rated Amperage	14A
	Frequency	50Hz
	Max. Output	4KW
	Rated Output	3.7KW
	Power Factor	1
	DC Output	DC12V,8.3A
Engine	Model	FC170F-2
	Туре	Single Cylinder, 4-Stroke, Forced Air Cooled
	Bore×Stroke	70mm×58mm
	Displacement	223cc
	Max. Output	4.9KW/3600RPM
	Fuel	Gasoline
	Fuel tank Capacity	15 Lit
	Rated Continuous Operation	8.6hr
	Lubricating Oil	SAE 10W-30
	Lubricating Oil Capacity	0.6 liter
	Starting System	Recoil
	Ignition system	T.C.I
	Spark Plug: Type	F7TC/F7RTC

POWER TOOLS

RH-4781







ݮ 🗠 😌 🏵 🚭





POWER TOOLS

Engine	Maximum Fuel Consumption Rate	1.74Lit/hr
Dimension	Net Dimension L×W×H	590×430×465mm
	Overall Dimension L×W×H	645×490×530mm
	Net Weight	43.5Kg
	Gross Weight	45.5Kg
Supplied in	Carton	
Include	2 Plug, 1 Spark Plug Sleeve,1 Rod, 12V DC Output Clip	