

**Gasoline Inverter Generator**  
**2.6 KW**

**RH-4794**

- 125cc, 4-stroke high power 3.4kw engine with outstanding performance
- Decreasing weight more than 20% compared with normal gasoline generator for better portability and less occupation
- Produces Output Pure Sine Wave AC and stable voltage to prevent from damaging to sensitive electronics equipment such as cell phone, laptop, and TV etc
- Super quiet as low as 60 DBA
- Equiped with two 220V AC outlet and one 12V DC outlet
- Economy Mode Switch Reduces wear and fuel consumption by adjusting RPM based on generator load
- The control unit instantly senses overload or short circuit and immediately shuts of engine to protect the generator and the load
- Low Oil Alert Helps to prevent engine damage
- Equipped with 4 wheels for easier movement
- Ideal for electronics equipment, RV, camping and home applications, small power tools



Model	RH-4794	
Generator	Type	Inverter Generator
	AC Voltage	220V/50Hz
	Max. Output	2.6KW
	Rated Output	2.3 KW
	Power Factor	1
	DC Output	DC12V/5A
	USB socket	5V/1A
	Engine	Model
Type		Air-Cooled, 4 cycle, OHV, Gasoline Engine
BorexStroke		52.4x57.8mm
Displacement		125cc
Max. Output		3.4KW/5500RPM
Fuel		GASOLINE
Fuel tank Capacity		7.5 Liters
Rated Continuous Operation		5 hr
Lubricating oil		SAE 10W30
Lubricating oil Capacity		0.9Liter
Starting System		Recoil Starter
Ignition system		CDI
Spark Plug: Type		A7RTC
Dimension	Net dimension LxWxH	614x341x506mm
	Overall dimension LxWxH	635x360x530mm
	Net Weight	33 Kg
	Gross Weight	36 Kg
Supplied in	Two Color Carton	
Include	Spark Plug Socket/Screw Driver/ Battery Charge Cable	