

AC Voltage Detector

Dual range

RH-9600

- Professional AC Voltage Detector with NCV Detector
- Dual range mode to adjust the sensitivity and choose AC voltage range between 12V-1000V and 48V-1000V
- Use alarm sound with different frequency and different color LED to indicate low, moderate or high sensitivity
- Distinguish the Neutral line, Live line, Breakpoint automatically
- LED illumination for working at night or in the low light area
- Low-Battery Indication warn you to replace the battery And meanwhile the auto power off feature can extend battery long life
- It is designed according to EN61010-1, EN61010-2-033, EN61326, and CAT.III1000V Concerning Safety Requirements



Model	RH-9600
Operating Temperature	0-40°C
Frequency	50-60Hz
Flash Light	White LED illumination Lamp
Alarm mode	Sound and light
Tester Type	Non-contact
AC voltage detection range	12-1000V, 48-1000V
Safety compliance	CE ROHS EN661010-1, EN61010-2-033, EN61326, CAT.III1000V
Battery	2×1.5V AAA
Net Weight	35gr
Supplied In	Ronix color box
Includes	2 pcs battery

